NFC PushRegistryWriter

Warning: This example was created for the NFC implementation provided on Series 40 devices, and may include use of features not yet available for NFC on Symbian devices.

The code shows a basic MIDlet that writes an NDEF (EXTERNAL_RTD) to a tag, in order to start an application. The application to be started requires the following line in the JAD-File:

```
MIDlet-Push-1: ndef:external_rtd?name=urn:nfc:ext:nfc-
research.at:pushreg,at.nfcresearch.wima.examples.PushReg,*
```

This example does NOT work in the Emulator of the Nokia 6131, but only on the phone! You can download ZIP with two NetBeans Project to try out the functionality: File:NDEFPush.zip.

```
package at.nfcresearch.wima.examples;

import javax.microedition.contactless.ContactlessException;
import javax.microedition.contactless.DiscoveryManager;
import javax.microedition.contactless.TargetListener;
import javax.microedition.contactless.TargetProperties;
import javax.microedition.contactless.TargetType;
import javax.microedition.contactless.ndef.NDEFMessage;
import javax.microedition.contactless.ndef.NDEFRecord;
import javax.microedition.contactless.ndef.NDEFRecordType;
import javax.microedition.contactless.ndef.NDEFTagConnection;
import javax.microedition.io.Connector;
import javax.microedition.midlet.*;
import javax.microedition.lcdui.*;

public class PushRegTagWriter extends MIDlet implements TargetListener, CommandListener
{

    // Display Items
    private Command exitCommand;
    private StringItem text;
    private Form form;

    public PushRegTagWriter() {

        // Display Items
        exitCommand = new Command("Exit", Command.EXIT, 1);
        form = new Form("NFC-Research.at: PushRegistry Tag Writer");

        form.addCommand(exitCommand);
        form.append("Touch Tag to write Ext-NDEF for PushRegistry start.");
        form.setCommandListener(this);


        // Registration of the Targetlistener
        // Look for ANY Type of RFID Tag that can be
        // read by the phone.
        try {
            DiscoveryManager dm = DiscoveryManager.getInstance();
            dm.addTargetListener(this, TargetType.RFID_TAG);
```


(C) Copyright Nokia 2014. All rights reserved.

```
        } catch (ContactlessException ce) {
            displayAlert("Unable to Register Targetlistener:" + ce.toString(),
AlertType.ERROR);
            Display.getDisplay(this).setCurrent(form);
        }
    }

    protected void startApp() {
        Display.getDisplay(this).setCurrent(form);
    }

    protected void pauseApp() {
    }

    protected void destroyApp(boolean bool) {

    }

    public void commandAction(Command cmd, Displayable disp) {
        if (cmd == exitCommand) {
            DiscoveryManager dm = DiscoveryManager.getInstance();
            dm.removeTargetListener(this, TargetType.RFID_TAG);
            destroyApp(false);
            notifyDestroyed();
        }


    }

    /**
     * Method called by the TargetListener in case a tag
     * was detected.
     * @param prop contains the array of tags found.
     */
    public void targetDetected(TargetProperties[] prop) {

        // if there is no information available on the tags
        // found, exit Method.
        if (prop.length == 0) {
            return;
        }

        // Create a new NDEF Connection in order
        // to write an NDEF EXT to the tag.
        NDEFTagConnection ndconn = null;
        try {
            // create an ndef tag connection.
            String ur =
prop[0].getUrl(Class.forName("javax.microedition.contactless.ndef.NDEFTagConnection"));

            // open the NDEF Connection
            ndconn = (NDEFTagConnection) Connector.open(ur);

            // now create the NDEFRecord
            NDEFRecordType myType = new NDEFRecordType(NDEFRecordType.EXTERNAL_RTD,
"urn:nfc:ext:nfc-research.at:pushreg");
            NDEFRecord myRec;
```


(C) Copyright Nokia 2014. All rights reserved.

```
            // create Data-Container for Tag
            myRec = new NDEFRecord(myType, null, null);

            NDEFRecord[] myRecArray = new NDEFRecord[]{myRec};
            NDEFMessage myMessage = new NDEFMessage(myRecArray);

            // write Information to Tag
            ndconn.writeNDEF(myMessage);

            displayAlert("Writing succeeded!", AlertType.INFO);
        } catch (Exception e) {
            displayAlert("Error Writing to Tag! " + e.toString(), AlertType.ERROR);
        }
        try {
            ndconn.close();
        } catch (Exception e) {
        }
    }

    private void displayAlert(String error, AlertType type) {
        Alert err = new Alert(form.getTitle(), error, null, type);
        Display.getDisplay(this).setCurrent(err, form);
    }
}
```


(C) Copyright Nokia 2014. All rights reserved.