Symbian OS Error Codes

This table is incomplete and contains only the first part of the error code listing.

Component	Name	Value	Suggested Text
E32 (E32ERR.H)	KErrNotFound	-1	Unable to find the specified object
E32 (E32ERR.H)	KErrGeneral	-2	General (unspecified) error
E32 (E32ERR.H)	KErrCancel	-3	The operation was cancelled
E32 (E32ERR.H)	KErrNoMemory	-4	Not enough memory. Close some applications and try again
E32 (E32ERR.H)	KErrNotSupported	-5	The operation requested is not supported
E32 (E32ERR.H)	KErrArgument	-6	Bad request
E32 (E32ERR.H)	KErrTotalLossOfPrecision	-7	Total loss of precision
E32 (E32ERR.H)	KErrBadHandle	-8	Bad object
E32 (E32ERR.H)	KErrOverflow	-9	Overflow
E32 (E32ERR.H)	KErrUnderflow	-10	Underflow
E32 (E32ERR.H)	KErrAlreadyExists	-11	Already exists
E32 (E32ERR.H)	KErrPathNotFound	-12	Unable to find the specified folder
E32 (E32ERR.H)	KErrDied	-13	Closed
E32 (E32ERR.H)	KErrInUse	-14	The specified object is currently in use by another program
E32 (E32ERR.H)	KErrServerTerminated	-15	Server has closed
E32 (E32ERR.H)	KErrServerBusy	-16	Server busy
E32 (E32ERR.H)	KErrCompletion	-17	Completion error
E32 (E32ERR.H)	KErrNotReady	-18	Not ready
E32 (E32ERR.H)	KErrUnknown	-19	Unknown error
E32 (E32ERR.H)	KErrCorrupt	-20	Corrupt
E32 (E32ERR.H)	KErrAccessDenied	-21	Access denied
E32 (E32ERR.H)	KErrLocked	-22	Locked
E32 (E32ERR.H)	KErrWrite	-23	Failed to write
E32 (E32ERR.H)	KErrDisMounted	-24	Wrong disk present
E32 (E32ERR.H)	KErrEof	-25	Unexpected end of file
E32 (E32ERR.H)	KErrDiskFull	-26	Disk full
E32 (E32ERR.H)	KErrBadDriver	-27	Bad device driver
E32 (E32ERR.H)	KErrBadName	-28	Bad name
E32 (E32ERR.H)	KErrCommsLineFail	-29	Comms line failed
E32 (E32ERR.H)	KErrCommsFrame	-30	Comms frame error
E32 (E32ERR.H)	KErrCommsOverrun	-31	Comms overrun error
E32 (E32ERR.H)	KErrCommsParity	-32	Comms parity error

(C) Copyright Nokia 2014. All rights reserved.

E32 (E32ERR.H)	KErrTimedOut	-33	Timed out
E32 (E32ERR.H)	KErrCouldNotConnect	-34	Failed to connect
E32 (E32ERR.H)	KErrCouldNotDisconnect	-35	Failed to disconnect
E32 (E32ERR.H)	KErrDisconnected	-36	Disconnected
E32 (E32ERR.H)	KErrBadLibraryEntryPoint	-37	Bad library entry point
E32 (E32ERR.H)	KErrBadDescriptor	-38	Bad descriptor
E32 (E32ERR.H)	KErrAbort	-39	Interrupted
E32 (E32ERR.H)	KErrTooBig	-40	Too big
E32 (E32ERR.H)	KErrDivideByZero	-41	Divide by zero
E32 (E32ERR.H)	KErrBadPower	-42	Batteries too low
E32 (E32ERR.H)	KErrDirFull	-43	Folder full
E32 (E32ERR.H)	KErrHardwareNotAvailable	-44	An operation cannot be performed because the necessary hardware is not available
E32 (E32ERR.H)	KErrSessionClosed	-45	The completion status when an outstanding client/server message is completed because a shared session has been closed
E32 (E32ERR.H)	KErrPermissionDenied	-46	Permission denied when attempting operation
E32 (E32ERR.H)	KErrExtensionNotSupported	-47	A requested extension function is not supported by the object concerned.
E32 (E32ERR.H)	KErrCommsBreak	-48	A break has occurred in a communications operation.
E32 (E32ERR.H)	KErrMsgBioMessageNotValid	-90	TBD
ETelFax (FAXSTD.H)	KFaxErrModemNotWorking	-101	Could not connect to the fax machine. The fax modem has failed
ETelFax (FAXSTD.H)	KFaxErrCannotConnect	-102	Could not connect to the fax machine
ETelFax (FAXSTD.H)	KFaxErrCSIorCIG	-103	Could not connect to the fax machine
ETelFax (FAXSTD.H)	KFaxErrDISorDTC	-104	Could not connect to the fax machine
ETelFax (FAXSTD.H)	KFaxErrFrameFail	-105	The connection to the fax machine has been broken
ETelFax (FAXSTD.H)	KFaxErrAtNegotiatedSpeed	-106	Could not connect to the fax machine
ETelFax (FAXSTD.H)	KFaxErrCFR	-107	Could not connect to the fax machine
ETelFax (FAXSTD.H)	KFaxErrMCF	-108	Could not connect to the fax machine

(C) Copyright Nokia 2014. All rights reserved.

ETelFax (FAXSTD.H)	KFaxErrCRP	-109	Could not connect to the fax machine
ETelFax (FAXSTD.H)	KFaxErrNoDial	-110	Could not connect to the fax machine. Could not dial fax number
ETelFax (FAXSTD.H)	KFaxErrNoDialTone	-111	Could not connect to the fax machine. No dial tone was detected
ETelFax (FAXSTD.H)	KFaxErrBusy	-112	Could not connect to the fax machine. The line is busy
ETelFax (FAXSTD.H)	KFaxErrNoAnswer	-113	Could not connect to the fax machine. The call was not answered
ETelFax (FAXSTD.H)	KFaxErrNoCarrier	-114	Could not connect to the fax machine. The call was not answered by a fax machine
ETelFax (FAXSTD.H)	KFaxErrRemoteCannotReceive	-115	Could not send to the fax machine. The fax machine is unable to receive faxes
ETelFax (FAXSTD.H)	KFaxErrCompression	-116	Panic
ETelFax (FAXSTD.H)	KFaxErrPageTooLong	-117	Panic
ETelFax (FAXSTD.H)	KFaxErrDCN	-118	Could not connect to the fax machine
ETelFax (FAXSTD.H)	KFaxErrRemoteDCN	-119	Could not connect to the fax machine
ETelFax (FAXSTD.H)	KFaxErrHDLC	-120	Could not connect to the fax machine
ETelFax (FAXSTD.H)	KFaxErrStopAndWait	-121	Panic
ETelFax (FAXSTD.H)	KFaxErrTrainStop	-122	Could not connect to the fax machine
ETelFax (FAXSTD.H)	KFaxErrReceiveTimeout	-123	Could not send to the fax machine. The connection has timed out
ETelFax (FAXSTD.H)	KFaxErrCannotEndData	-124	The connection to the fax machine has been broken
ETelFax (FAXSTD.H)	KFaxErrEOP	-125	Could not connect to the fax machine
ETelFax (FAXSTD.H)	KFaxErrMPS	-126	Could not connect to the fax machine
ETelFax (FAXSTD.H)	KFaxErrNoReceiveMode	-127	Could not connect to the fax machine
ETelFax (FAXSTD.H)	KFaxErrCannotAnswer	-128	Could not connect to the fax machine
ETelFax (FAXSTD.H)	KFaxErrPrematureHangup	-129	Could not receive fax. The fax machine ended the call
ETelFax (FAXSTD.H)	KFaxErrModemResponse	-130	Could not connect to the fax machine

(C) Copyright Nokia 2014. All rights reserved.

ETelFax (FAXSTD.H)	KFaxErrPrematureOK	-131	Could not connect to the fax machine
ETelFax (FAXSTD.H)	KFaxErrNoFinalOK	-132	Could not connect to the fax machine
ETelFax (FAXSTD.H)	KFaxErrUnknownPageCode	-133	Could not connect to the fax machine
ETelFax (FAXSTD.H)	KFaxErrNoHangup	-134	Could not connect to the fax machine
ETelFax (FAXSTD.H)	KFaxErrNoNegotiate	-135	Could not connect to the fax machine
ETelFax (FAXSTD.H)	KFaxErrModemDisconnect	-136	Could not connect to the fax machine
ETelFax (FAXSTD.H)	KFaxErrWrongModemType	-137	Could not connect to the fax machine
ETelFax (FAXSTD.H)	KFaxErrTrainFail	-138	Could not connect to the fax machine
ETelFax (FAXSTD.H)	KFaxTransmitterStalled	-139	Could not connect to the fax machine
ETelFax (FAXSTD.H)	KFaxReceiverOverflow	-140	Could not connect to the fax machine
ETelFax (FAXSTD.H)	KFaxCannotOpenPort	-141	Could not connect to the fax machine
ETelFax (FAXSTD.H)	KFaxCannotCloseStore	-142	Could not connect to the fax machine
ETelFax (FAXSTD.H)	KFaxCannotOpenStore	-143	Could not connect to the fax machine
ETelFax (FAXSTD.H)	KFaxThreadError	-144	Could not connect to the fax machine
ETelFax (FAXSTD.H)	KFaxFileSessionError	-145	Could not connect to the fax machine
ETelFax (FAXSTD.H)	KFaxLogCreateError	-146	Could not connect to the fax machine
ETelFax (FAXSTD.H)	KFaxFileSeeKError	-147	Could not connect to the fax machine
ETelFax (FAXSTD.H)	KFaxPDDError	-148	Could not connect to the fax machine
ETelFax (FAXSTD.H)	KFaxLDDError	-149	Could not connect to the fax machine
ETelFax (FAXSTD.H)	KFaxC32Error	-150	Could not connect to the fax machine
ETelFax (FAXSTD.H)	KFaxCommsServerError	-151	Could not connect to the fax machine
ETelFax (FAXSTD.H)	KFaxCommsPortError	-152	Could not connect to the fax machine
ETelFax (FAXSTD.H)	KFaxCancelRequested	-153	Could not connect to the fax machine
ETelFax (FAXSTD.H)	KFaxNoClass2Xon	-154	Could not connect to the fax machine
ETelFax (FAXSTD.H)	KFaxConfigError	-155	Could not connect to the fax machine
ETelFax (FAXSTD.H)	KFaxCannotAutodetect	-156	Could not connect to the fax machine

(C) Copyright Nokia 2014. All rights reserved.

ETelFax (FAXSTD.H)	KCannotFindFirstPage	-157	Could not connect to the fax machine
ETelFax (FAXSTD.H)	KFaxBadInitialization	-158	Could not connect to the fax machine
ETelFax (FAXSTD.H)	KFaxOnlyJustAutoDetected	-159	Could not connect to the fax machine
ETelFax (FAXSTD.H)	KFaxBelowMinSpeed	-160	Could not connect to the fax machine
ETelFax (FAXSTD.H)	KFaxPollingUnsupported	-161	Could not connect to the fax machine
ETelFax (FAXSTD.H)	KFaxNothingToPoll	-162	Could not connect to the fax machine
ETelFax (FAXSTD.H)	KfaxEtelServerError	-163	Could not connect to the fax machine
EmailPop (MIUT_ERR.H)	KPop3CannotConnect	-170	The POP3 server refused to allow a connection
EmailPop (MIUT_ERR.H)	KPop3InvalidUser	-171	The POP3 server refused to allow a connection. Check your mailbox username
EmailPop (MIUT_ERR.H)	KPop3InvalidLogin	-172	The POP3 server refused to allow a connection. Check your mailbox username and password
EmailPop (MIUT_ERR.H)	KPop3CannotCreateApopLogonString	-173	Could not create secure logon string. Mailbox server may not support secure logon
EmailPop (MIUT_ERR.H)	KPop3ProblemWithRemotePopServer	-174	Problem communicating with POP3 server
EmailPop (MIUT_ERR.H)	KPop3CannotOpenServiceEntry	-175	Panic
EmailPop (MIUT_ERR.H)	KPop3CannotSetRequiredFolderContext	-176	Panic
EmailPop (MIUT_ERR.H)	KPop3InvalidApopLogin	-177	Panic
Email Sockets (MIUT_ERR.H)	KImsKErrorDNSNotFound	-180	Could not find a DNS server. Please check the DNS address in the internet control panel
Email Sockets (MIUT_ERR.H)	KImsKErrorControlPanelLocked	-181	Could not connect to internet. Please ensure the internet control panel Or equivalent description to internet control panel is closed

(C) Copyright Nokia 2014. All rights reserved.

Email Sockets (MIUT_ERR.H)	KImskErrorISPOrIAPRecordNotFound	-182	TBD
Email Sockets (MIUT_ERR.H)	KImskErrorActiveSettingIsDifferent	-183	Unable to connect using the specified IAP, already connected to the Internet using a different IAP
Email Sockets (MIUT_ERR.H)	KImskSecuritySettingsFailed	-184	TBD
Sockets (INSOCK.H)	KErrNetUnreach	-190	Could not connect to the network. Currently unreachable
Sockets (INSOCK.H)	KErrHostUnreach	-191	Could not connect to the specified server
Sockets (INSOCK.H)	KErrNoProtocolOpt	-192	The specified server refuses the selected protocol
Sockets (INSOCK.H)	KErrUrgentData	-193	Panic
Email IMAP4 (MIUT_ERR.H)	KErrImapConnectFail	-200	Could not connect to IMAP4 server
Email IMAP4 (MIUT_ERR.H)	KErrImapServerFail	-201	The connection to the IMAP4 server has been broken
Email IMAP4 (MIUT_ERR.H)	KErrImapServerParse	-202	Panic
Email IMAP4 (MIUT_ERR.H)	KErrImapServerBusy	-203	The IMAP4 server refused to allow connection. The server is currently busy
Email IMAP4 (MIUT_ERR.H)	KErrImapServerVersion	-204	Could not connect to the IMAP server. The IMAP server is of the wrong version
Email IMAP4 (MIUT_ERR.H)	KErrImapSendFail	-205	Could not transmit to the IMAP4 server
Email IMAP4 (MIUT_ERR.H)	KErrImapBadLogon	-206	The IMAP4 server refused to allow a connection. Check your mailbox username and password
Email IMAP4 (MIUT_ERR.H)	KErrImapSelectFail	-207	Panic
Email IMAP4 (MIUT_ERR.H)	KErrImapWrongFolder	-208	Could not select an IMAP4 folder
Email IMAP4 (MIUT_ERR.H)	KErrImapServerNoSecurity	-209	TBD
Email IMAP4 (MIUT_ERR.H)	KErrImapServerLoginDisabled	-210	Login for this IMAP4 server has been

(C) Copyright Nokia 2014. All rights reserved.

(MIUT_ERR.H)			disabled
Email IMAP4 (MIUT_ERR.H)	KErrImapTLSNegotiateFailed	-211	A secure connection cannot be made to this server
Email IMAP4 (MIUT_ERR.H)	KErrImapCantDeleteFolder	-212	This folder cannot be deleted
Email IMAP4 (MIUT_ERR.H)	KDmssUnknownErr	-221	TBD
Email IMAP4 (MIUT_ERR.H)	KDmssMailboxUnavailableErr	-222	TBD
Email IMAP4 (MIUT_ERR.H)	KDmssActionAbortedErr	-223	TBD
Email IMAP4 (MIUT_ERR.H)	KDmssActionNotTakenErr	-224	TBD
Email IMAP4 (MIUT_ERR.H)	KDmssCmdUnrecognisedErr	-225	TBD
Email IMAP4 (MIUT_ERR.H)	KDmssSyntaxErrorErr	-226	TBD
Email IMAP4 (MIUT_ERR.H)	KDmssCmdNotImplementedErr	-227	TBD
Email IMAP4 (MIUT_ERR.H)	KDmssBadSequenceErr	-228	TBD
Email IMAP4 (MIUT_ERR.H)	KDmssParamNotImplementedErr	-229	TBD
Email IMAP4 (MIUT_ERR.H)	KDmssMailboxNoAccessErr	-230	TBD
Email IMAP4 (MIUT_ERR.H)	KDmssExceededStorageErr	-231	TBD
Email IMAP4 (MIUT_ERR.H)	KDmssMailboxNameErr	-232	TBD
Email IMAP4 (MIUT_ERR.H)	KDmssTransactionFailedErr	-233	TBD
Email IMAP4 (MIUT_ERR.H)	KDmssTimeOutErr	-234	TBD
Email SMTP (MIUT_ERR.H)	KSmtpNoMailFromErr	-240	Could not send email due to an invalid return email address. Check your email address in your account settings
Email SMTP (MIUT_ERR.H)	KSmtpUnknownErr	-241	Problem while sending email
Email SMTP (MIUT_ERR.H)	KSmtpBadMailFromAddress	-242	Email message has an invalid "From" address

(C) Copyright Nokia 2014. All rights reserved.

Email SMTP (MIUT_ERR.H)	KSmtpBadRcptToAddress	-243	Email message has an invalid "To", "Cc" or "Bcc" address
Email SMTP (MIUT_ERR.H)	KSmtpLoginRefused	-244	SMTP server refused to allow connection
Email SMTP (MIUT_ERR.H)	KSmtpNoMsgsToSendWithActiveSettings	-245	Could not send email. The messages are destined for an account different from the currently connected one.
Email SMTP (MIUT_ERR.H)	KErrSmtpTLSNegotiateFailed	-246	Secure connection failed. Server may not accept secure connections or certificates may be expired.
Email SMTP (MIUT_ERR.H)	KImcmHTMLPartNotPopulated	-250	TBD
Email SMTP (MIUT_ERR.H)	KImcmInvalidMessageStructure	-251	TBD
Email SMTP (MIUT_ERR.H)	KErrPop3TLSNegotiateFailed	-260	TBD
	//BaseScript Parser		
Access Point Engine (?.H)	KErrInvalidColumn	-300	Attempting to read or write a column which does not exists.
Access Point Engine (?.H)	KErrInvalidBearer	-301	The given bearer is not valid.
Access Point Engine (?.H)	KErrInvalidDatabaseType	-302	The type of the database is not valid
Access Point Engine (?.H)	KErrInvalidName	-303	The name of the AP is not valid (length = 0)
Access Point Engine (?.H)	KErrDescOverflow	-304	TBD
Access Point Engine (?.H)	KErrNullPointerPassed	-305	The passed pointer was invalid = NULL
Access Point Engine (?.H)	KErrInvalidFilterType	-310	The filter is not valid
Access Point Engine (?.H)	KErrInvalidBearerType	-311	The bearer is not valid
Access Point Engine (?.H)	KErrInvalidIspRequest	-312	The ISP type given is invalid
Access Point Engine (?.H)	KErrValueUnspecified	-323	Used when the requested value was not specified in the

(C) Copyright Nokia 2014. All rights reserved.

			database
Access Point Engine (?.H)	KApSelectionCanceled	-350	TBD
Access Point Engine (?.H)	KTxtNotOverriden	-351	TBD
Access Point Engine (?.H)	KErrInvalidTextId	-355	TBD
Access Point Engine (?.H)	KErrActiveApDbObserverNotFound	-500	Can be BIO Messaging "KBspInvalidMessage"
Bio Messaging (BSP.H)	KBspInvalidMessage	-500	Corrupt message cannot be read.
Bio Messaging (BSP.H)	KBspSmartMessageInvalidToken	-501	Corrupt message cannot be read.
Bio Messaging (BSP.H)	KBspSmartMessageNoParserDefined	-502	Unknown message type cannot be read.
//Access Point Parser			
Bio Messaging (IACPERR.H)	KIacpUnknownSmsType	-510	Unknown message type cannot be read.
Bio Messaging (IACPERR.H)	KIacpBIOMsgTypeNotSupported	-511	Unknown message type cannot be read.
Bio Messaging (IACPERR.H)	KiacpMandatoryDataNotSet	-512	Corrupt message cannot be read.
Bio Messaging (IACPERR.H)	KIacpUnknownMailProtocol	-513	Mailbox configuration message refers to an unknown protocol.
Bio Messaging (IACPERR.H)	KIacpErrRightToken	-514	Corrupt message cannot be read.
Bio Messaging (IACPERR.H)	KIacpErrLeftToken	-515	Corrupt message cannot be read.
Bio Messaging (IACPERR.H)	KIacpErrSmsDataNotParsed	-516	Corrupt message cannot be read.
Bio Messaging (IACPERR.H)	KIacpErrSmsDataNotRestored	-517	Corrupt message cannot be read.
Bio Messaging (IACPERR.H)	KIacpScriptErrISPNotFound	-518	Mailbox configuration message specifies an unknown Internet Access Point.
Bio Messaging (IACPERR.H)	KIacpErrScriptNotDefined	-519	Message script error.
Bio Messaging (IACPERR.H)	KIacpErrScriptNotFoundInDB	-520	Message script error.
Bio Messaging			

(C) Copyright Nokia 2014. All rights reserved.

(IACPERR.H)	KIacpErrScriptAlreadyAdd	-521	Message script error.
Sockets (INSOCK.H)	KErrWouldBlock	-1000	Panic
//Basic Application and Framework Library			
BAFL (BASCHED.H)	KErrExtended	-1000	
BAFL (BASCHED.H)	KErrExtendedWithText	-1001	
BAFL (BASCHED.H)	KLeaveWithoutAlert	-1002	
BAFL (BASCHED.H)	KLeaveExit	-1003	
	//Telephony Error Codes		
Etel (ETEL.H)	KErrEtelNotCallOwner	-2000	Panic
Etel (ETEL.H)	KErrEtelDuplicatePhoneName	-2001	Panic
Etel (ETEL.H)	KErrEtelAlreadyCallOwner	-2002	Panic
Etel (ETEL.H)	KErrEtelNoCarrier	-2003	Problem communicating receiving device. Call was unexpectedly dropped
Etel (ETEL.H)	KErrEtelBusyDetected	-2004	Phone number is busy. Wait before trying again
Etel (ETEL.H)	KErrEtelNoClientInterestedInThisCall	-2005	Panic
Etel (ETEL.H)	KErrEtelInitialisationFailure	-2006	Panic
Etel (ETEL.H)	KErrEtelCallNotActive	-2007	Panic
Etel (ETEL.H)	KErrEtelNoAnswer	-2008	Call was not answered
Etel (ETEL.H)	KErrEtelNoDialTone	-2009	Panic
Etel (ETEL.H)	KErrEtelConfigPortFailure	-2010	Panic
Etel (ETEL.H)	KErrEtelFaxChunkNotCreated	-2011	Panic
Etel (ETEL.H)	KErrEtelNotFaxOwner	-2012	Panic
Etel (ETEL.H)	KErrEtelPortNotLoanedToClient	-2013	Panic
Etel (ETEL.H)	KErrEtelWrongModemType	-2014	Panic
Etel (ETEL.H)	KErrEtelUnknownModemCapability	-2015	Panic
Etel (ETEL.H)	KErrEtelAnswerAlreadyOutstanding	-2016	Panic
Etel (ETEL.H)	KErrEtelModemNotDetected	-2017	Panic
Etel (ETEL.H)	KErrEtelModemSettingsCorrupt	-2018	Panic
	// netdial script errors		
Networking (ND_ERR.H)	KErrExitNoModem	-3001	No response from phone. Ensure phone is switched on
Networking (ND_ERR.H)	KErrExitModemError	-3002	Problem communicating with Internet service's modem
Networking (ND_ERR.H)	KErrExitLoginFail	-3003	Internet username or password is incorrect.
Networking (ND_ERR.H)	KErrExitScriptTimeOut	-3004	Internet service login script timed out. Internet service login script may be incorrect.

(C) Copyright Nokia 2014. All rights reserved.

Networking (ND_ERR.H)	KErrExitScriptError	-3005	Problem with Internet service login script. Internet service login script may be incorrect.
// netdial database error			
Networking (ND_ERR.H)	KErrNetDialDatabaseDefaultUndefined	-3006	
Networking (ND_ERR.H)	KErrNetDialDatabaseTypeUnknown	-3007	
Networking (ND_ERR.H)	KErrNetDialDatabaseNotFound	-3008	
Networking (ND_ERR.H)	KErrNetDialHscsdNotSupported	-3009	
TCP/IP (IN_IFACE.H)	KErrIfAuthenticationFailure	-3050	Internet username or password is incorrect
TCP/IP (IN_IFACE.H)	KErrIfAuthNotSecure	-3051	Internet service server only allows plain text authentication. This is currently disabled.
TCP/IP (IN_IFACE.H)	KErrIfAccountDisabled	-3052	Could not connect to Internet service. Your account has been disabled
TCP/IP (IN_IFACE.H)	KErrIfRestrictedLogonHours	-3053	Could not connect to Internet service. Your account is only active during restricted hours
TCP/IP (IN_IFACE.H)	KErrIfPasswdExpired	-3054	Could not connect to Internet service. Your Internet password has expired
TCP/IP (IN_IFACE.H)	KErrIfNoDialInPermission	-3055	Could not connect to Internet service. Your do not have dial-in permission
TCP/IP (IN_IFACE.H)	KErrIfChangingPassword	-3056	Panic
TCP/IP (IN_IFACE.H)	KErrIfCallbackNotAcceptable	-3057	Could not connect to Internet service. Callback is not supported
TCP/IP (IN_IFACE.H)	KErrIfDNSNotFound	-3058	Could not find specified Internet server
TCP/IP (IN_IFACE.H)	KErrIfLRDBadLine	-3059	Bad line to Internet service dropped
TCP/IP (IN_IFACE.H)	KErrIfNoServerPresent	-3060	Panic
TCP/IP (IN_IFACE.H)	KErrIfRemoteDisconnected	-3061	Panic
//Multimode telephony errors that will be generated by TSY			
Multimode Telephony (ETELMMERR.H)	KErrMMEtelWrongMode	-3201	Client has requested a mode-specific API service and the phone is currently in the wrong mode.
Multimode Telephony	KErrMMEtelFailedDueToModeChange	-3202	Error code to cater for requests that fail because the mode

(C) Copyright Nokia 2014. All rights reserved.

(ETELMMERR.H)	KErrMMEtelFailedDueToModeChange	-3202	changes mid-way during servicing that request
Multimode Telephony (ETELMMERR.H)	KErrMMEtelRemoteEndTermination	-3203	Remote user (or network) has terminated an ongoing call.
Multimode Telephony (ETELMMERR.H)	KErrMMEtelSmsFormatNotSupported	-3204	Client requested a message format that is not supported by TSY anor phone.
Multimode Telephony (ETELMMERR.H)	KErrMMEtelFeatureCodeNotSet	-3205	Client requests a service whose feature code has not been programmed e.g. Call Forwarding.
Multimode Telephony (ETELMMERR.H)	KErrMMEtelNetworkNotResponding	-3206	Network has failed to respond to an MS initiated request e.g. "flash info"
Multimode Telephony (ETELMMERR.H)	KErrMMEtelCallForbidden	-3207	Client requests a call to a destination that is forbidden.
Multimode Telephony (ETELMMERR.H)	KErrMMEtelMaxReached	-3208	The maximum number of entries in astore has been reached.
Multimode Telephony (ETELMMERR.H)	KErrMMEtelCallTerminated	-3209	Remote user (or network) has terminated an ongoing call.
Multimode Telephony (ETELMMERR.H)	KErrMMEtelFormatNotSupported	-3210	The client requested a message format that is not supported by TSY anor phone.
Multimode Telephony (ETELMMERR.H)	KErrMMEtelHiddenEntry	-3211	The phonebook entry is hidden.This is a USIM phonebook specific error.
Multimode Telephony (ETELMMERR.H)	KErrMMEtelFallbacktoVoice	-3212	The request to answer a multimedia call has failed because the network can now only support voice.
Multimode Telephony (ETELMMERR.H)	KErrMMEtelMacVerificationFailed	-3213	Authentication derived MAC does not match locally calculated MAC
Multimode Telephony (ETELMMERR.H)	KErrMMEtelSqnVerificationFailed	-3214	Authentication derived SQN value is not in the expected range
Multimode Telephony (ETELMMERR.H)	KErrMMEtelAuthenticateFailed	-3215	Authenticate command failed
//Error codes for use with Smart card application APIs.			
			Application cannot be

(C) Copyright Nokia 2014. All rights reserved.

Multimode Telephony (ETELMMERR.H)	KErrMMEtelScMaxApplicationsActive	-3216	activated as maximum number of applications already active.
Multimode Telephony (ETELMMERR.H)	KErrMMEtelScNoInfo NonVolatileMemoryUnchanged	-3217	No information given, the state of the non-volatile memory is unchanged.
Multimode Telephony (ETELMMERR.H)	KErrMMEtelScNoInfo NonVolatileMemoryChanged	-3218	No information given, the state of the non-volatile memory is changed.
Multimode Telephony (ETELMMERR.H)	KErrMMEtelScReturnedDataCorrupt	-3219	Part of the returned data may be corrupt.
Multimode Telephony (ETELMMERR.H)	KErrMMEtelScEofReached	-3220	End of file reached before reading requested number of bytes or records have been read.
Multimode Telephony (ETELMMERR.H)	KErrMMEtelScFileInvalidated	-3221	Selected file is invalidated.
Multimode Telephony (ETELMMERR.H)	KErrMMEtelScNoMemory	-3222	The smart card had a memory problem when executing the command.
Multimode Telephony (ETELMMERR.H)	KErrMMEtelScWrongLength	-3223	Wrong length
Multimode Telephony (ETELMMERR.H)	KErrMMEtelScGeneral	-3224	Technical problem, no precise diagnosis
Multimode Telephony (ETELMMERR.H)	KErrMMEtelScIncompatibleFileStructure	-3225	Command incompatible with file structure
Multimode Telephony (ETELMMERR.H)	KErrMMEtelScReferencedDataInvalidated	-3226	Referenced data invalidated
Multimode Telephony (ETELMMERR.H)	KErrMMEtelScFunctionNotSupported	-3227	Function not supported
Multimode Telephony (ETELMMERR.H)	KErrMMEtelScFileNotFound	-3228	File not found
Multimode Telephony (ETELMMERR.H)	KErrMMEtelScRecordNotFound	-3229	Record not found
Multimode Telephony (ETELMMERR.H)	KErrMMEtelScReferencedDataNotFound	-3230	Referenced data not found
Multimode Telephony (ETELMMERR.H)	KErrMMEtelScApplicationNotActive	-3231	Application not activate.
//CDMA network errors that will be generated by networks			
Multimode Telephony (ETELMMERR.H)	KErrCdmaSmsAddressVacant	-3256	SMS destination address is valid but not currently allocated to

(C) Copyright Nokia 2014. All rights reserved.

			an SMS terminal.
Multimode Telephony (ETELMMERR.H)	KErrCdmaSmsAddressTranslationFailure	-3257	SMS destination address is invalid.
Multimode Telephony (ETELMMERR.H)	KErrCdmaSmsNetworkResourceShortage	-3258	Network transmissionfailed due to lack of network resource or link capacity.
Multimode Telephony (ETELMMERR.H)	KErrCdmaSmsNetworkFailure	-3259	A network node failed, a link failed or a required operation failed.
Multimode Telephony (ETELMMERR.H)	KErrCdmaSmsInvalidTeleserviceId	-3260	SMS Teleservice ID is either not known or not supported.
Multimode Telephony (ETELMMERR.H)	KErrCdmaSmsOtherNetworkProblem	-3261	A network problem other than identified by above error codes.
Multimode Telephony (ETELMMERR.H)	KErrCdmaSmsNoPageResponse	-3262	The addressed MS-based SME is known but it does not respond to a page.
Multimode Telephony (ETELMMERR.H)	KErrCdmaSmsDestinationBusy	-3263	The addressed MS-based SME is SMS capable but is currently engaged in a call, a service or a call mode that precludes the use of SMS.
Multimode Telephony (ETELMMERR.H)	KErrCdmaSmsNoAcknowledgement	-3264	The destination SME does not acknowledge receipt of the SMS delivery.
Multimode Telephony (ETELMMERR.H)	KErrCdmaSmsDestinationResourceShortage	-3265	A required terminal resource (e.g.memory) is not available to process this message.
Multimode Telephony (ETELMMERR.H)	KErrCdmaSmsDeliveryPostponed	-3266	Delivery is not currently possible but SMS notification is pending.
Multimode Telephony (ETELMMERR.H)	KErrCdmaSmsOtherNetworkProblem	-3267	The addressed destination is out of service for an extended period of time.
Multimode Telephony (ETELMMERR.H)	KErrCdmaSmsDestinationNoLongerAtAddress	-3268	The MS based SME is no longer at the temporary SMS routing address.
Multimode Telephony (ETELMMERR.H)	KErrCdmaSmsOtherTerminalProblem	-3269	A terminal problem other than identified by the above error codes.
Multimode Telephony			There is no channel available or there is

(C) Copyright Nokia 2014. All rights reserved.

(ETELMMERR.H)	KErrCdmaSmsRadioInterfaceResourceShortage	-3320	available or there is radio congestion at this time.
Multimode Telephony (ETELMMERR.H)	KErrCdmaSmsRadioInterfaceIncompatibility	-3321	The MS for an MS-based SME is operating in a mode that does not support SMS at this time.
Multimode Telephony (ETELMMERR.H)	KErrCdmaSmsOtherRadioInterfaceProblem	-3322	A radio interface problem other than identified by the above error codes.
Multimode Telephony (ETELMMERR.H)	KErrCdmaSmsEncodingProblem	-3352	The size of a parameter or field is not what is expected.
Multimode Telephony (ETELMMERR.H)	KErrCdmaSmsOriginationDenied	-3353	The originating MIN is not recognized, the originating address is not allowed for the originating MIN, the ESN doesn't match the originating MIN, the origination is not authorized, the originating address is not recognized, etc.
Multimode Telephony (ETELMMERR.H)	KErrCdmaSmsTerminationDenied	-3354	The destination is not authorized to receive the SMS message, the MC refused the message, the destination SME refused the message, the destination is not authorized for a required supplementary service, etc.
Multimode Telephony (ETELMMERR.H)	KErrCdmaSmsSupplServiceNotSupported	-3355	The originating supplementary service is not known or supported, the sender is not authorized for an originating supplementary service, etc.
Multimode Telephony (ETELMMERR.H)	KErrCdmaSmsSmsNotSupported	-3356	SMS is not supported by an addressed functional entity.
Multimode Telephony (ETELMMERR.H)	KErrCdmaSmsMissingExpectedParameter	-3358	An optional parameter is missing that is required for a particular function.
Multimode Telephony (ETELMMERR.H)	KErrCdmaSmsMissingMandatoryParameter	-3359	A parameter is missing that is mandatory for a particular message.
Multimode Telephony			A known parameter

(C) Copyright Nokia 2014. All rights reserved.

(ETELMMERR.H)	KErrCdmaSmsUnrecognizedParameterValue	-3360	has an unknown or unsupported value.
Multimode Telephony (ETELMMERR.H)	KErrCdmaSmsUnexpectedParameterValue	-3361	A known parameter has a known, but unexpected value.
Multimode Telephony (ETELMMERR.H)	KErrCdmaSmsUserDataSizeError	-3362	The User Data size is too large for access technology, transport network, or call mode, etc. The User Data size is not what is expected for the indicated teleservice.
Multimode Telephony (ETELMMERR.H)	KErrCdmaSmsOtherGeneralProblem	-3363	Other general problems.
Generic Connection Agent (GENCONNERROR.H)	KErrGenConnDatabaseDefaultUndefined	-3606	CommDb Error
Generic Connection Agent (GENCONNERROR.H)	KErrGenConnDatabaseTypeUnknown	-3607	CommDb Error
Generic Connection Agent (GENCONNERROR.H)	KErrGenConnDatabaseNotFound	-3608	CommDb Error
(EXTERROR.H)	KErrEtelGsmBase	-4000	
TelephonyGSMRadioResource NetworkErrors (EXTERROR.H)	KErrGsmRRUnspecifedAbnormalRelease	-4001	Temporary network failure. Try again later.
TelephonyGSMRadioResource* NetworkErrors (EXTERROR.H)	KErrGsmRRChannelUnacceptable	-4002	Temporary network failure. Try again later.
TelephonyGSMRadioResource NetworkErrors (EXTERROR.H)	KErrGsmRRTimerExpired	-4003	Temporary network failure. Try again later.
TelephonyGSMRadioResource NetworkErrors (EXTERROR.H)	KErrGsmRRNoActivityOnRadioPath	-4004	Temporary network failure. Try again later.
TelephonyGSMRadioResource NetworkErrors (EXTERROR.H)	KErrGsmRRPreEmptiveRelease	-4005	Temporary network failure. Try again later.
TelephonyGSMRadioResource NetworkErrors (EXTERROR.H)	KErrGsmRRCallAlreadyCleared	-4065	Temporary network failure. Try again later.
TelephonyGSMRadioResource NetworkErrors (EXTERROR.H)	KErrGsmRRInvalidMessage	-4095	Temporary network failure. Try again later.
TelephonyGSMRadioResource NetworkErrors (EXTERROR.H)	KErrGsmRRNonExistentMessage	-4097	No network support for requested operation.

(C) Copyright Nokia 2014. All rights reserved.

TelephonyGSMRadioResource NetworkErrors (EXTERROR.H)	KErrGsmRRIncompatibleMessageWithCallState	-4098	Temporary network failure. Try again later.
TelephonyGSMRadioResource NetworkErrors (EXTERROR.H)	KErrGsmRRInvalidInformationElement	-4100	Temporary network failure. Try again later.
TelephonyGSMRadioResource NetworkErrors (EXTERROR.H)	KErrGsmRRUnspecifiedProtocolError	-4111	Temporary network failure. Try again later.
(EXTERROR.H)	KErrGsmMobilityManagementBase = KErrGsmRadioResourceBase	-4128	Offset for the GSM mobility management errors.
TelephonyGSMMobilityManagement NetworkErrors (EXTERROR.H)	KErrGsmMMUnallocatedTmsi	-4129	Temporary network failure. Try again later.
TelephonyGSMMobilityManagement NetworkErrors (EXTERROR.H)	KErrGsmMMImsiUnknownInHlr	-4130	Operation is not allowed. Contact cellular network operator.
TelephonyGSMMobilityManagement NetworkErrors (EXTERROR.H)	KErrGsmMMIllegalMs	-4131	Phone is blacklisted. Contact cellular network operator.
TelephonyGSMMobilityManagement NetworkErrors (EXTERROR.H)	KErrGsmMMImsiUnknownInVlr	-4132	Temporary network failure. Try again later.
TelephonyGSMMobilityManagement NetworkErrors (EXTERROR.H)	KErrGsmMMImeiNotAccepted	-4133	Phone failure.
TelephonyGSMMobilityManagement NetworkErrors (EXTERROR.H)	KErrGsmMMIllegalMe	-4134	Phone is blacklisted. Contact cellular network operator.
GPRS (ETELPCKT.H)	KErrGprsServiceNotAllowed	-4135	Failed to connect to the GPRS network
GPRS (ETELPCKT.H)	KErrGprsAndNonGprsServicesNotAllowed	-4136	Failed to connect to the mobile network
GPRS (ETELPCKT.H)	KErrGprsMSIdentityCannotBeDerivedByTheNetwork	-4137	Identity could not be derived by the network
GPRS (ETELPCKT.H)	KErrGprsMSImplicitlyDetached	-4138	Your device was disconnected from the GPRS network.
TelephonyGSMMobilityManagement NetworkErrors (EXTERROR.H)	KErrGsmMMPlmnNotAllowed	-4139	Roaming is not allowed in this area.
TelephonyGSMMobilityManagement NetworkErrors (EXTERROR.H)	KErrGsmMMLocationAreaNotAllowed	-4140	Roaming is not allowed in this area.
TelephonyGSMMobilityManagement NetworkErrors (EXTERROR.H)	KErrGsmMMRoamingNotAllowedInThisLocationArea	-4141	Roaming is not allowed in this area.

(C) Copyright Nokia 2014. All rights reserved.

..			
GPRS (ETELPCKT.H)	KErrGprsMSCTemporarilyNotReachable	-4144	GPRS MSC temporary not reachable
..			
TelephonyGSMMobilityManagement NetworkErrors (EXTERROR.H)	KErrGsmMMNetworkFailure	-4145	Temporary network failure. Try again later.
TelephonyGSMMobilityManagement NetworkErrors (EXTERROR.H)	KErrGsmMMCongestion	-4150	Network busy.
..			
GPRS (ETELPCKT.H)	KErrGprsLlcOrSndcpFailure	-4153	Your connection to Internet was dropped.
GPRS (ETELPCKT.H)	KErrGprsInsufficientResources	-4154	Network overloaded.
GPRS (ETELPCKT.H)	KErrGprsMissingorUnknownAPN	-4155	"Could not connect to Internet service. Callback is not supported""""
GPRS (ETELPCKT.H)	KErrGprsUnknownPDPAddress	-4156	The address for the Internet provider is not correct.
GPRS (ETELPCKT.H)	KErrGprsUserAuthenticationFailure	-4157	Failed to identify the user.
GPRS (ETELPCKT.H)	KErrGprsActivationRejectedByGGSN	-4158	Can't connect to the Internet.
GPRS (ETELPCKT.H)	KErrGprsActivationRejected	-4159	Can't connect to the Internet (not enough credit available on SIM).
..			
TelephonyGSMMobilityManagement NetworkErrors (EXTERROR.H)	KErrGsmMMServiceOptionNotSupported	-4160	Operation is not presently supported by the network.
TelephonyGSMMobilityManagement NetworkErrors (EXTERROR.H)	KErrGsmMMServiceOptionNotSubscribed	-4161	Service not subscribed. Contact cellular network operator.
TelephonyGSMMobilityManagement NetworkErrors (EXTERROR.H)	KErrGsmMMServiceOptionTemporaryOutOfOrder	-4162	Service temporarily out of use. Try again later.
..			
GPRS (ETELPCKT.H)	KErrGprsNSAPIAlreadyUsed	-4163	NS API already used
GPRS (ETELPCKT.H)	KErrGprsRegularContextDeactivation	-4164	Regular context deactivation
GPRS (ETELPCKT.H)	KErrGprsQoSNotAccepted	-4165	The requested quality of service was not

(C) Copyright Nokia 2014. All rights reserved.

			granted.
..			
TelephonyGSMMobilityManagement NetworkErrors (EXTERROR.H)	KErrGsmMMCallCanNotBeIdentified	-4166	Temporary network failure. Try again later.
..			
GPRS (ETELPCKT.H)	KErrGprsReactivationRequested	-4167	Reactivation requested
GPRS (ETELPCKT.H)	KErrGprsFeatureNotSupported	-4168	This is not supported.
GPRS (ETELPCKT.H)	KErrGprsSemanticErrorInTFTOperation	-4169	Semantic error in the TFT operation.
GPRS (ETELPCKT.H)	KErrGprsSyntacticalErrorInTFTOperation	-4170	Syntactical error in the TFT operation.
GPRS (ETELPCKT.H)	KErrGprsUnknownPDPContext	-4171	PDP context activation request is not active.
GPRS (ETELPCKT.H)	KErrGprsSemanticErrorsInPacketFilters	-4172	Semantic error(s) in packet filter(s) of the TFT.
GPRS (ETELPCKT.H)	KErrGprsSyntacticalErrorInPacketFilters	-4173	Syntactical error(s) in packet filter(s) of the TFT.
GPRS (ETELPCKT.H)	KErrGprsPDPContextWithoutTFTAlreadyActivated	-4174	GPRS network has already activated a PDP context without TFT.
GPRS (ETELPCKT.H)	KErrUmtsQoSNotAvailable	-4177	QoS not available.
GPRS (ETELPCKT.H)	KErrUmtsMaxNumOfContextExceededByPhone	-4178	Maximum number of PDP contexts supported by phone exceeded.
GPRS (ETELPCKT.H)	KErrUmtsMaxNumOfContextExceededByNetwork	-4179	Maximum number of PDP contexts supported by the network exceeded.
GPRS (ETELPCKT.H)	KErrGprsOfflineMode	-4180	Phone is in offline mode.
..			
TelephonyGSMMobilityManagement NetworkErrors (EXTERROR.H)	KErrGsmMMSemanticErrorInMessage	-4223	Temporary network failure. Try again later.
TelephonyGSMMobilityManagement NetworkErrors (EXTERROR.H)	KErrGsmMMMandatoryInformationElementError	-4224	Temporary network failure. Try again later.
TelephonyGSMMobilityManagement NetworkErrors (EXTERROR.H)	KErrGsmMMNonExistentMessageType	-4225	No network support for requested operation.
TelephonyGSMMobilityManagement NetworkErrors (EXTERROR.H)	KErrGsmMMIncompatibleMessageWithProtocolState	-4226	Temporary network failure. Try again later.
TelephonyGSMMobilityManagement	KErrGsmMMNonExistentInformationElement	-4227	Temporary network

(C) Copyright Nokia 2014. All rights reserved.

NetworkErrors (EXTERROR.H)	KErrGsmMMNonExistentInformationElement	-4227	failure. Try again later.
TelephonyGSMMobilityManagement NetworkErrors (EXTERROR.H)	KErrGsmMMConditionalIEError	-4228	Temporary network failure. Try again later.
TelephonyGSMMobilityManagement NetworkErrors (EXTERROR.H)	KErrGsmMMIncompatibleMessageWithCallState	-4229	Temporary network failure. Try again later.
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCUnassignedNumber	-4257	Invalid phone number. Check the number and try again.
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCNoRouteToTransitNetwork	-4258	Temporary network failure. Try again later.
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCNoRouteToDestination	-4259	Invalid phone number. Check the number and try again.
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCChannelUnacceptable	-4262	Temporary network failure. Try again later.
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCOperatorDeterminedBarring	-4264	Operation is not allowed. Contact cellular network operator.
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCUserBusy	-4273	Number is busy. Try again later.
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCUserNotResponding	-4274	The remote user is not currently reachable. Try again later.
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCUserAlertingNoAnswer	-4275	The remote user is not currently reachable. Try again later.
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCCallRejected	-4276	Short network failure. Try again immediately.
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCNumberChanged	-4277	Number has changed. Check the number and try again.
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCNonSelectedUserClearing	-4282	Unknown network failure. Try again later.
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCDestinationOutOfOrder	-4283	Temporary network failure. Try again later.
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCInvalidNumberFormat	-4284	Invalid phone number. Check the number and try again.
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCFacilityRejected	-4285	Operation is not supported. Contact cellular network operator.
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCResponseToStatusEnquiry	-4286	Blank
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCNormalUnspecified	-4287	Unknown network failure. Try again later.

(C) Copyright Nokia 2014. All rights reserved.

TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCNoChannelAvailable	-4290	Network busy.
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCNetworkOutOfOrder	-4294	Serious cellular network failure. Please contact the cellular network operator.
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCTemporaryFailure	-4297	Short network failure. Try again immediately.
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCSwitchingEquipmentCongestion	-4298	Network busy.
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCAccessInformationDiscarded	-4299	Temporary network failure. Try again later.
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCRequestedChannelNotAvailable	-4300	Network busy.
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCResourceNotAvailable	-4303	Network busy.
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCQualityOfServiceNotAvailable	-4305	Service can not be provided.
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCRequestedFacilityNotSubscribed	-4306	Check operator services or connection settings.
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCIncomingCallsBarredInCug	-4311	Incoming calls are not allowed within closed user group.
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCBearerCapabilityNotAuthorised	-4313	Unauthorised operation.
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCBearerCapabilityNotCurrentlyAvailable	-4314	Requested service is not presently available. Try again later.
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCServiceNotAvailable	-4319	Check operator services or connection settings.
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCBearerServiceNotImplemented	-4321	Check operator services or connection settings.
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCChannelTypeNotImplemented	-4322	Check operator services or connection settings.
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCAcmGreaterThanAcmMax	-4324	Blank
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCRequestedFacilityNotImplemented	-4325	Check operator services or connection settings.
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCOnlyRestrictedDigitalInformationBCAvailable	-4326	Blank
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCServiceNotImplemented	-4335	Check operator services or connection

(C) Copyright Nokia 2014. All rights reserved.

NetworkErrors (EXTERROR.H)			settings.
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCInvalidCallReferenceValue	-4337	Blank
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCChannelDoesNotExist	-4338	Temporary network failure. Try again later.
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCSuspendedCallExistsButCallIdentityDoesNotWork	-4339	Blank
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCCallIdentityInUse	-4340	Blank
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCNoCallSuspended	-4341	Blank
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCRequestedCallIdentityAlreadyCleared	-4342	Blank
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCUserNotInCug	-4343	Only calls within closed user group allowed.
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCIncompatibleDestination	-4344	Check connection type in connection settings.
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCInvalidTransitNetworkSelection	-4347	Temporary network failure. Try again later.
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCIncompatibleSegmentedMessage	-4350	Blank
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCSemanticallyIncorrectMessage	-4351	Blank
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCInvalidMandatoryInformation	-4352	Check operator services or connection settings.
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCNonExistentMessageType	-4353	Blank
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCIncompatibleMessageInProtocolState	-4354	Blank
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCNonExistentInformationElement	-4355	Blank
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCConditionalIEError	-4356	Blank
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCIncompatibleMessageInCallState	-4357	Blank
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCRecoveryOnTimerExpiry	-4358	Blank
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCUnspecifiedProtocolError	-4367	Temporary network failure. Try again later.
TelephonyGSMCallControl NetworkErrors (EXTERROR.H)	KErrGsmCCUnspecifiedInterworkingError	-4383	Operation is not presently supported by

(C) Copyright Nokia 2014. All rights reserved.

NetworkErrors (EXTERROR.H)			the network.
..			
TelephonyGSMSupplementaryServices (EXTERROR.H)	KErrGsmSSUnknownSubscriber	-4385	Unknown subscriber. Contact cellular network operator.
TelephonyGSMSupplementaryServices (EXTERROR.H)	KErrGsmSSIllegalSubscriber	-4393	Unknown subscriber. Contact cellular network operator.
TelephonyGSMSupplementaryServices (EXTERROR.H)	KErrGsmSSBearerServiceNotProvisioned	-4394	Service is not provisioned.
TelephonyGSMSupplementaryServices (EXTERROR.H)	KErrGsmSSTeleserviceNotProvisioned	-4395	Service is not provisioned.
TelephonyGSMSupplementaryServices (EXTERROR.H)	KErrGsmSSIllegalEquipment	-4396	Blank
TelephonyGSMSupplementaryServices (EXTERROR.H)	KErrGsmSSCallBarred	-4397	Calls are barred by the operator. Contact cellular network operator.
TelephonyGSMSupplementaryServices (EXTERROR.H)	KErrGsmSSIllegalOperation	-4400	Operation is not supported. Contact cellular network operator.
TelephonyGSMSupplementaryServices (EXTERROR.H)	KErrGsmSSErrorStatus	-4401	Operation is not supported. Contact cellular network operator.
TelephonyGSMSupplementaryServices (EXTERROR.H)	KErrGsmSSNotAvailable	-4402	Operation is not supported. Contact cellular network operator.
TelephonyGSMSupplementaryServices (EXTERROR.H)	KErrGsmSSSubscriptionViolation	-4403	Operation is not allowed. Contact cellular network operator.
TelephonyGSMSupplementaryServices (EXTERROR.H)	KErrGsmSSIncompatibility	-4404	The requested supplementary service is incompatible.
TelephonyGSMSupplementaryServices (EXTERROR.H)	KErrGsmSSFacilityNotSupported	-4405	Operation is not supported. Contact cellular network operator.
TelephonyGSMSupplementaryServices (EXTERROR.H)	KErrGsmSSAbsentSubscriber	-4411	Blank
TelephonyGSMSupplementaryServices (EXTERROR.H)	KErrGsmSSSystemFailure	-4418	Temporary network failure. Try again later.
TelephonyGSMSupplementaryServices (EXTERROR.H)	KErrGsmSSDataMissing	-4419	Parameter in the service request is missing.
TelephonyGSMSupplementaryServices	KErrGsmSSUnexpectedDataValue	-4420	Unknown parameter in

(C) Copyright Nokia 2014. All rights reserved.

(EXTERROR.H)	KErrGsmSSUnexpectedDataValue	-4420	the service request.
TelephonyGSMSupplementaryServices (EXTERROR.H)	KErrGsmSSPasswordRegistrationFailure	-4421	Wrong service password.
TelephonyGSMSupplementaryServices (EXTERROR.H)	KErrGsmSSNegativePasswordCheck	-4422	Wrong service password.
TelephonyGSMSupplementaryServices (EXTERROR.H)	KErrGsmSSPasswordAttemptsViolation	-4427	Too many times wrong service password.
TelephonyGSMSupplementaryServices (EXTERROR.H)	KErrGsmSSUnknownAlphabet	-4455	Incompatible service language or alphabets.
TelephonyGSMSupplementaryServices (EXTERROR.H)	KErrGsmSSUssdBusy	-4456	Blank
TelephonyGSMSupplementaryServices (EXTERROR.H)	KErrGsmSSMaxNumMptyParticipants	-4510	Too many participants of a multiparty call.
TelephonyGSMSupplementaryServices (EXTERROR.H)	KErrGsmSSResourcesUnavailable	-4511	Temporarily out of network resources when requesting the service.
..			>
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSUnassignedNumber	-4513	Invalid phone number. Check the number and try again.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSOperatorDeterminedBarring	-4520	Operation is not allowed. Contact cellular network operator.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSCallBarred	-4522	Call barred.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSReserved	-4523	Blank
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSNetworkFailure	-4529	Temporary network failure. Try again later.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSShortMessageTransferRejected	-4533	Short network failure. Try again immediately.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSMemoryCapacityExceeded	-4534	Temporary network failure. Try again later.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSDestinationOutOfOrder	-4539	Temporary network failure. Try again later.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSUnidentifiedSubscriber	-4540	Unknown subscriber. Contact cellular network operator.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSFacilityRejected	-4541	Operation is not supported. Contact cellular network operator.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSUnknownSubscriber	-4542	Unknown subscriber. Contact cellular network operator.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSNetworkOutOfOrder	-4550	Serious cellular network failure. Please contact the cellular

(C) Copyright Nokia 2014. All rights reserved.

			network operator.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSTemporaryFailure	-4553	Temporary network failure. Try again later.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSCongestion	-4554	Network busy.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSResourcesUnavailable	-4559	Network busy.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSRequestedFacilityNotSubscribed	-4562	Service not subscribed. Contact cellular network operator.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSRequestedFacilityNotImplemented	-4581	Check operator services or connection settings.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSInvalidShortMessageTransferReferenceValue	-4593	Operation is not presently supported by the network.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSUnspecifiedInvalidMessage	-4607	Unknown network failure. Try again later.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSInvalidMandatoryInformation	-4608	Error in message content.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSNonExistentMessageType	-4609	Operation is not presently supported by the network.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSIncompatibleMessageWithSmsProtocolState	-4610	Operation is not presently supported by the network.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSInformationElementNotImplemented	-4611	Message type is not presently supported by the network.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSUnspecifiedProtocolError	-4623	Unknown network failure. Try again later.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSUnspecifiedInterworkingError	-4639	Operation is not presently supported by the network.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSTelematicInterworkingNotSupported	-4640	Operation is not presently supported by the network.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSShortMessageType0NotSupported	-4641	Message type is not presently supported by the network.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSCannotReplaceShortMessage	-4642	Cannot deliver the message to the destination.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSUnspecifiedPIDError	-4655	Unknown network failure. Try again later.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSDataCodingSchemeNotSupported	-4656	Incompatible message language or alphabets.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSMessageClassNotSupported	-4657	Message type is not presently supported by the network.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSUnspecifiedDCSError	-4671	Unknown network failure. Try again later.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSCommandCannotBeActioned	-4672	Operation cannot be performed.

(C) Copyright Nokia 2014. All rights reserved.

TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSCommandNotSupported	-4673	Operation is not presently supported by the network.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSUnspecifiedCommandError	-4687	Unknown network failure. Try again later.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSTpduNotSupported	-4688	Operation is not presently supported by the network.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSServiceCentreBusy	-4704	Service centre is busy. Try again later.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSNoSCSubscription	-4705	No service centre. Check messaging settings.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSSCSystemFailure	-4706	Service centre failure. Try again later.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSInvalidSMEAddress	-4707	Service centre failure. Try again later.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSDestinationSMEBarred	-4710	The destination is barred.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSDuplicateSM	-4711	Blank
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSTPVPFNotSupported	-4712	Short message validity period not supported by the network.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSTPVPNotSupported	-4713	Short message validity period not supported by the network.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSSimSMSStorageFull	-4720	Short message storage in SIM card is full.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSNoSMSStorageCapabilityInSim	-4721	No short message storage capability in SIM card.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSErrorInMS	-4722	Error receiving the short message.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSMemCapacityExceeded	-4723	No space to store the short message.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSSimAppToolkitBusy	-4724	SIM is busy performing another operation.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSUnspecifiedErrorCause	-4767	Unknown network failure. Try again later.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSFailureInME	-4812	Error in receiving the short message.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSServiceOfMSReserved	-4813	Busy because of short message operation.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSOperationNotAllowed	-4814	Operation is not allowed. Contact cellular network operator.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSOperationNotSupported	-4815	Phone is not supporting the operation.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSInvalidPDUModeParameter	-4816	Blank
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSInvalidTextModeParameter	-4817	Blank

(C) Copyright Nokia 2014. All rights reserved.

TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSSimNotInserted	-4822	Insert SIM card.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSSimPin1Required	-4823	PIN1 is required to continue.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSPhoneToSimLockRequired	-4824	Blank
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSSimFailure	-4825	SIM card failure. Replace the SIM card.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSSimBusy	-4826	SIM card is busy performing another operation.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSSimWrong	-4827	Wrong SIM card. Replace the SIM card.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSSimPuk1Required	-4828	PUK1 code is required to continue.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSPin2Required	-4829	PIN2 is required to continue.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSPuk2Required	-4830	PUK2 code is required to continue.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSMemoryFailure	-4832	Memory failure. Try again.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSInvalidMemoryIndex	-4833	Memory failure. Try again.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSMemoryFull	-4834	Memory is full. Remove some messages and try again.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSUnknownSCAddress	-4842	Blank
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSNoNetworkService	-4843	Service not available.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSNetworkTimeout	-4844	Temporary network failure. Try again later.
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSCnmaAckNotExpected	-4852	Blank
TelephonyGSMSms (EXTERROR.H)	KErrGsmSMSUnknownError	-5012	Temporary network failure. Try again later.
WLan (wlanerrorcodes.h)	KErrWlanInternalError	-30171	A failure inside WLAN subsystem has occurred. Typically caused by an unexpected WLAN HW event.
WLan (wlanerrorcodes.h)	KErrWlanOpenAuthFailed	-30172	WLAN AP has refused 802.11 open system authentication.
WLan (wlanerrorcodes.h)	KErrWlanSharedKeyAuthRequired	-30173	WLAN AP requires 802.11 shared key authentication.
WLan (wlanerrorcodes.h)	KErrWlanSharedKeyAuthFailed	-30174	802.11 shared key authentication has failed.
WLan (wlanerrorcodes.h)	KErrWlanWpaAuthRequired	-30175	WLAN AP requires Wi-Fi Protected Access security butthe IAP doesn't have matching settings.

(C) Copyright Nokia 2014. All rights reserved.

WLan (wlanerrorcodes.h)	KErrWlanWpaAuthFailed	-30176	Wi-Fi Protected Access authentication has failed.
WLan (wlanerrorcodes.h)	KErrWlan802dot1xAuthFailed	-30177	Legacy 802.1x authentication has failed.
WLan (wlanerrorcodes.h)	KErrWlanIllegalWpaPskKey	-30178	Wi-Fi Protected Access authentication w/ a preshared key has failed.
WLan (wlanerrorcodes.h)	KErrWlanWpaCounterMeasuresActive	-30179	Wi-Fi Protected Access connections are not allowed as countermeasures are active due to MIC failures.
WLan (wlanerrorcodes.h)	KErrWlanNetworkNotFound	-30180	No WLAN APs matching the IAP settings have been found.
WLan (wlanerrorcodes.h)	KErrWlanIllegalEncryptionKeys	-30181	The IAP has an illegal key WEP key configuration.
WLan (wlanerrorcodes.h)	KErrWlanRoamingFailed	-30182	Roaming between WLAN APs has failed irreversibly.
WLan (wlanerrorcodes.h)	KErrWlanNetworkLost	-30183	Connection to the WLAN network has unexpectedly been lost.
WLan (wlanerrorcodes.h)	KErrWlanPskModeRequired	-30184	WLAN AP requires Wi-Fi Protected Access authentication w/ a preshared key.
WLan (wlanerrorcodes.h)	KErrWlanEapModeRequired	-30185	WLAN AP requires Wi-Fi Protected Access authentication w/ EAP.
WLan (wlanerrorcodes.h)	KErrWlanEapSimFailed	-30186	EAP-SIM authentication has failed.
WLan (wlanerrorcodes.h)	KErrWlanEapTlsFailed	-30187	EAP-TLS authentication has failed.
WLan (wlanerrorcodes.h)	KErrWlanEapPeapFailed	-30188	EAP-PEAP authentication has failed.
WLan (wlanerrorcodes.h)	KErrWlanEapMsChapv2	-30189	EAP-MSCHAPv2 authentication has failed.
WLan (wlanerrorcodes.h)	KErrWlanEapAkaFailed	-30190	EAP-AKA authentication has failed.
WLan (wlanerrorcodes.h)	KErrWlanEapTtlsFailed	-30191	EAP-TTLS authentication has failed.

(C) Copyright Nokia 2014. All rights reserved.

WLan (wlanerrorcodes.h)	KErrWlanLeapFailed	-30192	EAP-LEAP authentication has failed.
WLan (wlanerrorcodes.h)	KErrWlanEapGtcFailed	-30193	EAP-GTC authentication has failed.
WLan (wlanerrorcodes.h)	KErrWlanSimNotInstalled	-30194	EAP-SIM/EAP-AKA authentication has failed due to a missing SIM card.
WLan (wlanerrorcodes.h)	KErrWlanNotSubscribed	-30195	EAP-SIM/EAP-AKA authentication has failed due to missing service subscription.
WLan (wlanerrorcodes.h)	KErrWlanAccessBarred	-30196	EAP-SIM/EAP-AKA authentication has failed due to user being barred from the service.
WLan (wlanerrorcodes.h)	KErrWlanPasswordExpired	-30197	EAP-MSCHAPv2 authentication has failed due to expired password.
WLan (wlanerrorcodes.h)	KErrWlanNoDialinPermissions	-30198	EAP-MSCHAPv2 authentication has failed due to permissions.
WLan (wlanerrorcodes.h)	KErrWlanAccountDisabled	-30199	EAP-MSCHAPv2 authentication has failed due to disabled account.
WLan (wlanerrorcodes.h)	KErrWlanRestrictedLogonHours	-30200	EAP-MSCHAPv2 authentication has failed due to restricted logon hours.

Resources

Download the error codes spreadsheet from here

The following errors are from a google cache of the NewLC error code list (the link is currently broken). Please integrate these into the table above.

[show details]

(C) Copyright Nokia 2014. All rights reserved.

(C) Copyright Nokia 2014. All rights reserved.